



## СБПБШп 19x2x1 ТУ У 31.3-00214534-008-2001

Signal blocking cables with copper conductors, with polyethylene insulation, in polyethylene sheath, with galvanized double-steel-tape armouring, in polyethylene hose

Designed for electrical installations of railway signaling, centralization, blocking and automation at a rated voltage of 380 V AC at frequency 50 Hz or 700 V DC

Cables are used for laying:

- in soil (trenches), in corrosion environment
- in places, where small mechanical impacts on cable are possible, including tensile forces

### TECHNICAL SPECIFICATIONS

|   |        |                 |
|---|--------|-----------------|
| Rated voltage   | V      | 380 / 700       |
| Number of pairs and nominal conductor diameter  |        | 19 x 1          |
| Electrical resistance of the conductor at 20 °C   | Ohm/km | 28.8            |
| Operating capacity, not more than   | nF/km  | 100.0           |
| Attenuation coefficient of pairs at a temperature of 20 °C, not more than                     | dB/km  | 0.94            |
| Coupling losses on near-end of cable between any pairs over a length of 300 m, not less than: |        |                 |
| • for 100% of the values  | dB     | 60.0            |
| • for 80% of the values   | dB     | 62.0            |
| Operating temperature range   | °C     | -50 ... +60     |
| Minimum bending radius by laying  | mm     | 312             |
| Cable outer diameter (for reference only) **  | mm     | 26              |
| Cable weight (approximate)  | kg/km  | 775             |
| Rated factory cable length and gross weight of the delivery on the drums                      | m, t   | # 14: 930 • 0.9 |

Notes:

When ordering it is necessary to agree the factory length of the product with the manufacturer

\*\* The external diameter may differ from the rated up to  $\pm 10\%$



## СБПБШп 19x2x1 ТУ У 31.3-00214534-008-2001

Signal blocking cables with copper conductors, with polyethylene insulation, in polyethylene sheath, with galvanized double-steel-tape armouring, in polyethylene hose

### CONSTRUCTION

1. Copper conductor
2. Polyethylene insulation
3. PET film winding
4. Polyethylene inner sheath
5. Double steel-tape armour
6. Bitumen layer
7. Polyethylene protection hose

Note: Pair twisting in the layer of core on the picture not shown.

